

**CRITICAL ITEMS LIST**

PROJECT: SRMS  
ASS'Y NOMENCLATURE: EEEU

SYSTEM: ELECTRICAL SUBSYSTEM  
ASS'Y P/N: 511401174-3E-5

SHEET: 1

FMEA REF.	FMEA REV.	NAME, QTY & DRAWING REF. DESIGNATION	FAILURE MODE AND CAUSE	FAILURE EFFECT ON END ITEM	HDWR / FUNC. 2/1R CRITICALITY RATIONALE FOR ACCEPTANCE SCREENS: A-PASS, B-PASS, C-PASS
3600	2	POWER CONDITIONER QTY-1 SCHEMATIC 2559002	<p>MODE: DEGRADED OUTPUT ON ONE OR MORE OUTPUT VOLTAGE.</p> <p>CAUSE(S): (1) OUTPUT FILTER FAILURE.</p>	<p>HIGH RIPPLE IN OUTPUT MAY CAUSE ERRATIC OPERATION OF IC'S RESULTING IN ERRATIC EE RESPONSE; IF DEGRADATION IS BAD ENOUGH, OVER-VOLTAGE OR OVER-CURRENT MAY TURN OFF EEEU. EFFECT SAME AS 3580.</p> <p>COULD HAVE MOTOR REVERSAL DURING COMMANDS. MOTOR MAY STALL OR SLIP CLUTCH.</p> <p>WORST CASE</p> <p>UNEXPECTED PAYLOAD MOTION. INCOMPLETE CAPTURE/RELEASE SEQUENCE. UNABLE TO RELEASE PAYLOAD. CREW ACTION REQ.</p> <p>REDUNDANT PATHS REMAINING</p> <p>BACKUP EE RELEASE.</p>	<p>DESIGN FEATURES</p> <p>-----</p> <p>TRANSFORMERS AND INDUCTORS ARE DESIGNED SPECIFICALLY FOR THE APPLICATION. THESE ARE TOROID - WOUND AND UTILIZE A FERRITE CORE MATERIAL. CHOICE OF WIRE SIZE AND OF INSULATION MATERIALS ENSURE THAT THE DERATING REQUIREMENTS OF SPAR-RMS-PA.003 ARE MET.</p> <p>ALL RESISTORS AND CAPACITORS USED IN THE DESIGN ARE SELECTED FROM ESTABLISHED RELIABILITY (ER) TYPES. LIFE EXPECTANCY IS INCREASED BY ENSURING THAT ALL ALLOWABLE STRESS LEVELS ARE DERATED IN ACCORDANCE WITH SPAR-RMS-PA.003. ALL CERAMIC AND ELECTROLYTIC CAPACITORS ARE ROUTINELY SUBJECTED TO RADIOGRAPHIC INSPECTION.</p>

RMS/ELEC - 1109

PREPARED BY:

MHW

SUPERSEDING DATE: 06 OCT 87

APPROVED BY: \_\_\_\_\_

DATE: 24 JUL 91

CIL REV: 2

**CRITICAL ITEMS LIST**

PROJECT: SRMS  
ASS'Y NOMENCLATURE: EEEU

SYSTEM: ELECTRICAL SUBSYSTEM  
ASS'Y P/N: 51140F1174-38-5

SHEET: 2

RMS/ELEC - 1110

FMEA REF.	FMEA REV.	NAME, QTY, & DRAWING REF. DESIGNATION	FAILURE MODE AND CAUSE	FAILURE EFFECT ON END ITEM	HOWR / FUNC. 2/1R CRITICALITY RATIONALE FOR ACCEPTANCE SCREENS: A-PASS, B-PASS, C-PASS
3600	2	POWER CONDITIONER QTY-1 SCHEMATIC 2559082	<p>MODE: DEGRADED OUTPUT ON ONE OR MORE OUTPUT VOLTAGE.</p> <p>CAUSE(S): (1) OUTPUT FILTER FAILURE.</p>	<p>HIGH RIPPLE IN OUTPUT MAY CAUSE ERRATIC OPERATION OF IC'S RESULTING IN ERRATIC EE RESPONSE; IF DEGRADATION IS BAD ENOUGH, OVER-VOLTAGE OR OVER-CURRENT MAY TURN OFF EEEU. EFFECT SAME AS 3500.</p> <p>COULD HAVE MOTOR REVERSAL DURING COMMANDS. MOTOR MAY STALL OR SLIP CLUTCH.</p> <p>WORST CASE ----- UNEXPECTED PAYLOAD MOTION. INCOMPLETE CAPTURE/RELEASE SEQUENCE. UNABLE TO RELEASE PAYLOAD. CREW ACTION REQ.</p> <p>REDUNDANT PATHS REMAINING ----- BACKUP EE RELEASE.</p>	<p>ACCEPTANCE TESTS ----- THE EEEU IS SUBJECTED TO THE FOLLOWING ACCEPTANCE ENVIRONMENTAL TESTING AS AN SRU.</p> <p>O VIBRATION: LEVEL AND DURATION REFERENCE TABLE 6</p> <p>O THERMAL: +70 DEGREES C TO -25 DEGREES C (1 1/2 CYCLES)</p> <p>THE EEEU IS INTEGRATED INTO THE END EFFECTOR AND IS FURTHER EXPOSED TO THE END EFFECTOR ACCEPTANCE TEST ENVIRONMENTS (VIBRATION AND THERMAL VACUUM).</p> <p>THE END EFFECTOR ASSEMBLY IS PART OF THE INTEGRATED RMS SYSTEM TESTS (TP516 RMS STRONGBACK TEST AND TP552 FLAT FLOOR TEST) WHICH VERIFIES THE ABSENCE OF THE FAILURE MODE.</p> <p>QUALIFICATION TESTS ----- THE EEEU IS SUBJECTED TO THE FOLLOWING SRU QUALIFICATION TEST ENVIRONMENTS.</p> <p>O VIBRATION: LEVEL AND DURATION - REFERENCE TABLE 6</p> <p>O SHOCK: 20G/11MS - 3 AXES (6 DIRECTIONS)</p> <p>O THERMAL: +81 DEGREES C TO -36 DEGREES C (6 CYCLES) 1 X 10<sup>4</sup>-6 TORR</p> <p>O HUMIDITY: TESTED IN THE END EFFECTOR HUMIDITY TEST.</p> <p>O EMC: MIL-STD-461 AS MODIFIED BY SI-E-0002 (TESTS CE01, CE03, CS01, CS02, CS06, RE01, RE02 (N/B) RS01).</p> <p>FLIGHT CHECKOUT ----- PDRS OPS CHECKLIST (ALL VEHICLES) JSC 16987</p>

PREPARED BY:

MFG

SUPERSEDING DATE: 06 OCT 87

APPROVED BY:

DATE: 24 JUL 91

CIL REV: 2

**CRITICAL ITEMS LIST**

PROJECT: SRMS  
ASS'Y NOMENCLATURE:

SYSTEM: ELECTRICAL SUBSYSTEM  
ASS'Y P/N: 51140F1174-36-5

SHEET: \_\_\_\_\_

FMEA REF.	FMEA REV.	NAME, QTY. & DRAWING REF. DESIGNATION	FAILURE MODE AND CAUSE	FAILURE EFFECT ON END ITEM	HOWR / FUNC. 2/1R CRITICALITY RATIONALE FOR ACCEPTANCE SCREENS: A-PASS, B-PASS, C-PASS
3600	2	POWER CONDITIONER QTY-1 SCHEMATIC 2559002	<p>MODE: DEGRADED OUTPUT ON ONE OR MORE OUTPUT VOLTAGE.</p> <p>CAUSE(S): (1) OUTPUT FILTER FAILURE.</p>	<p>HIGH RIPPLE IN OUTPUT MAY CAUSE ERRATIC OPERATION OF IC'S RESULTING IN ERRATIC EE RESPONSE- IF DEGRADATION IS BAD ENOUGH, OVER-VOLTAGE OR OVER-CURRENT MAY TURN OFF EEU. EFFECT SAME AS 3500.</p> <p>COULD HAVE MOTOR REVERSAL DURING COMMANDS. MOTOR MAY STALL OR SLIP CLUTCH.</p> <p>WORST CASE ----- UNEXPECTED PAYLOAD MOTION. INCOMPLETE CAPTURE/RELEASE SEQUENCE. UNABLE TO RELEASE PAYLOAD. CREW ACTION REQ.</p> <p>REDUNDANT PATHS REMAINING ----- BACKUP EE RELEASE.</p>	<p>QA/INSPECTIONS -----</p> <p>UNITS ARE MANUFACTURED UNDER DOCUMENTED QUALITY CONTROLS. THESE CONTROLS ARE EXERCISED THROUGHOUT DESIGN PROCUREMENT, PLANNING, RECEIVING, PROCESSING, FABRICATION, ASSEMBLY, TESTING AND SHIPPING OF THE UNITS. MANDATORY INSPECTION POINTS ARE EMPLOYED AT VARIOUS STAGES OF FABRICATION ASSEMBLY AND TEST. GOVERNMENT SOURCE INSPECTION IS INVOKED AT VARIOUS CONTROL LEVELS.</p> <p>EEE PARTS INSPECTION IS PERFORMED AS REQUIRED BY SPAR-RMS-PA.003. EACH EEE PART IS QUALIFIED AT THE PART LEVEL TO THE REQUIREMENTS OF THE APPLICABLE SPECIFICATION. ALL EEE PARTS ARE 100% SCREENED AND BURNED IN, AS A MINIMUM, AS REQUIRED BY SPAR-RMS-PA.003, BY THE SUPPLIER. ADDITIONALLY, EEE PARTS ARE 100% RE-SCREENED IN ACCORDANCE WITH REQUIREMENTS, BY AN INDEPENDENT SPAR APPROVED TESTING FACILITY. DPA IS PERFORMED AS REQUIRED BY PA.003 ON A RANDOMLY SELECTED 5% OF PARTS, MAXIMUM 5 PIECES, MINIMUM 3 PIECES FOR EACH LOT NUMBER/DATE CODE OF PARTS RECEIVED.</p> <p>WIRE IS PROCURED TO SPECIFICATION MIL-W-22759 OR MIL-W-81361 AND INSPECTED AND TESTED TO NASA JSCM0080 STANDARD NUMBER 95A.</p> <p>RECEIVING INSPECTION VERIFIES THAT ALL PARTS RECEIVED ARE AS IDENTIFIED IN THE PROCUREMENT DOCUMENTS, THAT NO PHYSICAL DAMAGE HAS OCCURRED TO PARTS DURING SHIPMENT, THAT THE RECEIVING DOCUMENTS PROVIDE ADEQUATE TRACEABILITY INFORMATION AND SCREENING DATA CLEARLY IDENTIFIES ACCEPTABLE PARTS.</p> <p>PARTS ARE INSPECTED THROUGHOUT MANUFACTURE AND ASSEMBLY AS APPROPRIATE TO THE MANUFACTURING STAGE COMPLETED. THESE INSPECTIONS INCLUDE,</p> <p>PRINTED CIRCUIT BOARD INSPECTION FOR TRACK SEPARATION, DAMAGE AND ADEQUACY OF PLATED THROUGH HOLES,</p> <p>COMPONENT MOUNTING INSPECTION FOR CORRECT SOLDERING, WIRE LOOPING, STRAPPING, ETC. OPERATORS AND INSPECTORS ARE TRAINED AND CERTIFIED TO NASA NHB 5300.4(3-1) STANDARD.</p> <p>CONFORMAL COATING INSPECTION FOR ADEQUATE PROCESSING IS PERFORMED USING ULTRAVIOLET LIGHT TECHNIQUES.</p> <p>POST P.C. BD. INSTALLATION INSPECTION, CLEANLINESS AND WORKMANSHIP (SPAR/GOVERNMENT REP. MANDATORY INSPECTION POINT)</p> <p>P.C. BD. INSTALLATION INSPECTION, CHECK FOR CORRECT BOARD INSTALLATION, ALIGNMENT OF BOARDS, PROPER CONNECTOR CONTACT MATING, WIRE ROUTING, STRAPPING OF WIRES ETC.,</p> <p>PRE-CLOSURE INSPECTION, WORKMANSHIP AND CLEANLINESS (SPAR/GOVERNMENT REP. - MANDATORY INSPECTION POINT)</p> <p>PRE-ACCEPTANCE TEST INSPECTION, WHICH INCLUDES AN AUDIT OF LOWER TIER INSPECTION COMPLETION, AS BUILT CONFIGURATION VERIFICATION TO AS DESIGN ETC., (MANDATORY INSPECTION POINT).</p>

RMS/ELEC - 1111

PREPARED BY: \_\_\_\_\_

HWG

SUPERCEDING DATE: 06 OCT 87

APPROVED BY: \_\_\_\_\_

DATE: 24 JUL 91

CIL REV: 2

**CRITICAL ITEMS LIST**

PROJECT: SRMS  
ASS'Y NOMENCLATURE: EEEU

SYSTEM: ELECTRICAL SUBSYSTEM  
ASS'Y P/N: 51160F1174-3E-5 SHEET: 4

FMEA REF.	FMEA REV.	NAME, QTY. & DRAWING REF. DESIGNATION	FAILURE MODE AND CAUSE	FAILURE EFFECT ON END ITEM	HOWR / FUNC. 2/1R CRITICALITY RATIONALE FOR ACCEPTANCE SCREENS: A-PASS, B-PASS, C-PASS
3600	2	POWER CONDITIONER QTY-1 SCHEMATIC 2559082	<p>MODE: DEGRADED OUTPUT ON ONE OR MORE OUTPUT VOLTAGE.</p> <p>CAUSE(S): (1) OUTPUT FILTER FAILURE.</p>	<p>HIGH RIPPLE IN OUTPUT MAY CAUSE ERRATIC OPERATION OF IC'S RESULTING IN ERRATIC EE RESPONSE. IF DEGRADATION IS BAD ENOUGH, OVER-VOLTAGE OR OVER-CURRENT MAY TURN OFF EEEU. EFFECT SAME AS 3580.</p> <p>COULD HAVE MOTOR REVERSAL DURING COMMANDS. MOTOR MAY STALL OR SLIP CLUTCH.</p> <p>WORST CASE ----- UNEXPECTED PAYLOAD MOTION. INCOMPLETE CAPTURE/RELEASE SEQUENCE. UNABLE TO RELEASE PAYLOAD. CREW ACTION REQ.</p> <p>REDUNDANT PATHS REMAINING ----- BACKUP EE RELEASE.</p>	<p>A TEST READINESS REVIEW (TRR) WHICH INCLUDES VERIFICATION OF TEST PERSONNEL, TEST DOCUMENTS, TEST EQUIPMENT CALIBRATION/ VALIDATION STATUS AND HARDWARE CONFIGURATION IS CONVENED BY QUALITY ASSURANCE IN CONJUNCTION WITH ENGINEERING, RELIABILITY, CONFIGURATION CONTROL, SUPPLIER AS APPLICABLE, AND THE GOVERNMENT REPRESENTATIVE, PRIOR TO THE START OF ANY FORMAL TESTING (ACCEPTANCE OR QUALIFICATION).</p> <p>ACCEPTANCE TESTING (ATP) INCLUDES AMBIENT PERFORMANCE, THERMAL AND VIBRATION TESTING, (SPAR/GOVERNMENT REP. - MANDATORY INSPECTION POINT).</p> <p>INTEGRATION OF UNIT TO END EFFECTOR ASSY - INSPECTIONS INCLUDE GROUNDING CHECKS, CONNECTERS FOR BENT OF PUSHBACK CONTACTS, VISUAL CLEANLINESS, INTERCONNECT WIRING ETC. AND POWER-UP TEST TO SPAR INSPECTION TEST PROCEDURE ITP-2510.</p> <p>PRE-ACCEPTANCE TEST INSPECTION, WHICH INCLUDES AN AUDIT OF LOWER TIER INSPECTION COMPLETION, AS BUILT CONFIGURATION VERIFICATION TO AS DESIGN ETC., (MANDATORY INSPECTION POINT).</p> <p>ACCEPTANCE TESTING (ATP) INCLUDES, AMBIENT, VIBRATION AND THERMAL-VAC TESTING, (SPAR/GOVERNMENT REP. - MANDATORY INSPECTION POINT)</p> <p>SRMS SYSTEMS INTEGRATION, THE INTEGRATION OF MECHANICAL ARM SUBASSEMBLIES AND THE FLIGHT CABIN EQUIPMENT TO FORM THE SRMS. INSPECTIONS ARE PERFORMED AT EACH PHASE OF INTEGRATION WHICH INCLUDES GROUNDING CHECKS, THRU WIRING CHECKS, WIRING ROUTING, INTERFACE CONNECTORS FOR BENT OR PUSH BACK CONTACTS ETC.</p> <p>SRMS SYSTEMS TESTING - STRONGBACK AND FLAT FLOOR AMBIENT PERFORMANCE TEST. (SPAR/GOVERNMENT REP. - MANDATORY INSPECTION POINT)</p>

RMS/ELEC - 1112

PREPARED BY:

MFVG

SUPERCEDING DATE: 06 OCT 87

APPROVED BY:

DATE: 26 JUL 91

CIL REV: 2

**CRITICAL ITEMS LIST**

PROJECT: SRMS  
ASS'Y NOMENCLATURE: EEEU

SYSTEM: ELECTRICAL SUBSYSTEM  
ASS'Y P/N: 511401174-36-3 SHEET: 5

FMEA REF.	FMEA REV.	NAME, QTY, & DRAWING REF. DESIGNATION	FAILURE MODE AND CAUSE	FAILURE EFFECT ON END ITEM	HOWR / FUNC. 2/1R CRITICALITY RATIONALE FOR ACCEPTANCE SCREENS: A-PASS, B-PASS, C-PASS
3600	2	POWER CONDITIONER QTY-1 SCHEMATIC 2559082	<p>MODE: DEGRADED OUTPUT ON ONE OR MORE OUTPUT VOLTAGE.</p> <p>CAUSE(S): (1) OUTPUT FILTER FAILURE.</p>	<p>HIGH RIPPLE IN OUTPUT MAY CAUSE ERRATIC OPERATION OF IC'S RESULTING IN ERRATIC EE RESPONSE; IF DEGRADATION IS BAD ENOUGH, OVER-VOLTAGE OR OVER-CURRENT MAY TURN OFF EEEU. EFFECT SAME AS 3580.</p> <p>COULD HAVE MOTOR REVERSAL DURING COMMANDS. MOTOR MAY STALL OR SLIP CLUTCH.</p> <p>WORST CASE ----- UNEXPECTED PAYLOAD MOTION. INCOMPLETE CAPTURE/RELEASE SEQUENCE. UNABLE TO RELEASE PAYLOAD. CREW ACTION REQ.</p> <p>REDUNDANT PATHS REMAINING ----- BACKUP EE RELEASE.</p>	<p>FAILURE HISTORY ----- THE FOLLOWING FAILURE ANALYSIS REPORT(S) ARE RELEVANT:</p> <p>FAR 3053: S/N 202 OCT 79</p> <p>DESCRIPTION ----- NOISE ON LOGIC COMMAND LINE DUE TO DESIGN ERROR</p> <p>CORRECTIVE ACTION ----- ECN 3501-D/2-3918, 3919 REPLACED OVERSTRESSED TRANS. 05, 06, 07, AND 08</p>

RMS/ELEC - 1113

**CRITICAL ITEMS LIST**

PROJECT: SRMS

SYSTEM: ELECTRICAL SUBSYSTEM

ASS'Y NOMENCLATURE: EEU

ASS'Y P/N: 51140F1174-38-5

SHEET: 6

RMS/ELEC - 1114

FMEA REF.	FMEA REV.	NAME, QTY, & DRAWING REF. DESIGNATION	FAILURE MODE AND CAUSE	FAILURE EFFECT ON END ITEM	HOWR / FUNC. 2/1R CRITICALITY	RATIONALE FOR ACCEPTANCE SCREENS: A-PASS, B-PASS, C-PASS
3600	2	POWER CONDITIONER QTY-1 SCHEMATIC 2559082	MODE: DEGRADED OUTPUT ON ONE OR MORE OUTPUT VOLTAGE.  CAUSE(S): (1) OUTPUT FILTER FAILURE.	HIGH RIPPLE IN OUTPUT MAY CAUSE ERRATIC OPERATION OF IC'S RESULTING IN ERRATIC EE RESPONSE. IF DEGRADATION IS BAD ENOUGH, OVER-VOLTAGE OR OVER-CURRENT MAY TURN OFF EEU. EFFECT SAME AS 3580.  COULD HAVE MOTOR REVERSAL DURING COMMANDS. MOTOR MAY STALL OR SLIP CLUTCH.  WORST CASE ----- UNEXPECTED PAYLOAD MOTION. INCOMPLETE CAPTURE/RELEASE SEQUENCE. UNABLE TO RELEASE PAYLOAD. CREW ACTION REQ.  REDUNDANT PATHS REMAINING ----- BACKUP EE RELEASE.		OPERATIONAL EFFECTS ----- EE DOES NOT OPERATE NOMINALLY WHEN COMMANDED. ARM REMAINS LIMP UNTIL EE MODE SWITCH IS TURNED OFF DURING AN AUTO CAPTURE SEQUENCE.  CREW ACTION ----- FOR ANY OFF NOMINAL OPERATION OF THE EE, THE EE MODE SWITCH SHOULD BE TURNED OFF. ATTEMPT TO CAPTURE IN THE ALTERNATE MODE. IF THE SNARES REMAIN OPEN, MANEUVER ARM AWAY FROM PAYLOAD. IF THE SNARES ARE PARTIALLY CLOSED, ATTEMPT RELEASE USING A PRIMARY EE MODE. IF SNARES OPEN, MANEUVER THE ARM AWAY FROM THE PAYLOAD; IF SNARES DON'T OPEN, ATTEMPT TO RELEASE IN BACKUP MODE. IF SNARES OPEN, MANEUVER ARM AWAY FROM THE PAYLOAD. MANEUVER ORBITER AWAY FROM PAYLOAD. IF SNARES CANNOT BE OPENED, IN ANY MODE, EVA CAN BE USED TO RELEASE THE PAYLOAD OR THE ARM/PAYLOAD COMBINATION CAN BE JETTISONED.  CREW TRAINING ----- CREW WILL BE TRAINED TO RECOGNIZE OFF NOMINAL EE OPERATIONS AND TO MANEUVER THE ORBITER AWAY FROM A FREE FLYING PAYLOAD AT ANY TIME DURING ARM OPERATIONS.  MISSION CONSTRAINT ----- WHEN CAPTURING A FREE FLYING PAYLOAD, THE EE MUST BE FAR ENOUGH AWAY FROM STRUCTURE TO PROHIBIT CONTACT REGARDLESS OF PAYLOAD ROTATIONS. THE EE MODE SWITCH SHOULD BE PLACED BACK IN THE OFF POSITION IMMEDIATELY AFTER THE SPEC DRIVE TIME HAS ELAPSED.  CMRSD OFFLINE ----- VERIFY NOMINAL EE OPERATION. VERIFY EEU BITE FLAG.  CMRSD ONLINE INSTALLATION ----- NONE  CMRSD ONLINE TURNAROUND ----- VERIFY NOMINAL EE OPERATION. VERIFY ABE DATA FOR EEU BITE AND ABE FAILURE WARNING.

PREPARED BY:

MFVG

SUPERCEDING DATE: 06 OCT 87

APPROVED BY:

DATE: 26 JUL 91

CIL REV: 2

**CRITICAL ITEMS LIST**

PROJECT: SRMS  
ASS'Y NOMENCLATURE: EEEU

SYSTEM: ELECTRICAL SUBSYSTEM  
ASS'Y P/N: 5114011174-1E-5

SHEET: 7

P/N REF.	REV.	NAME, QTY, & DRAWING REF. DESIGNATION	FAILURE MODE AND CAUSE	FAILURE EFFECT OR END ITEM	HDWR / FUNC. 2/1R CRITICALITY	RATIONALE FOR ACCEPTANCE SCREENS: A-PASS, B-PASS, C-PASS
3600	2	POWER CONDITIONER QTY-1 SCHEMATIC 2559082	MODE: DEGRADED OUTPUT ON ONE OR MORE OUTPUT VOLTAGE.  CAUSE(S): (1) OUTPUT FILTER FAILURE.	HIGH RIPPLE IN OUTPUT MAY CAUSE ERRATIC OPERATION OF IC'S RESULTING IN ERRATIC EE RESPONSE. IF DEGRADATION IS BAD ENOUGH, OVER-VOLTAGE OR OVER-CURRENT MAY TURN OFF EEEU. EFFECT SAME AS 3580.  COULD HAVE MOTOR REVERSAL DURING COMMANDS. MOTOR MAY STALL OR SLIP CLUTCH.  WORST CASE ..... UNEXPECTED PAYLOAD MOTION. INCOMPLETE CAPTURE/RELEASE SEQUENCE, UNABLE TO RELEASE PAYLOAD. CREW ACTION REQ.  REDUNDANT PATHS REMAINING ..... BACKUP EE RELEASE.		

RMS/ELEC - 1115

PREPARED BY:

NFWG

SUPERCEDING DATE: 06 OCT 87

APPROVED BY:

DATE: 24 JUL 91

CIL REV: 2